

## EA 1128 Power Amplifier



### Key features

25 watts (RMS) per channel with 4 speaker outputs

Ideal for corporate, education and training, or worship environments.

4 stereo inputs on the rear panel, with another two microphone inputs on the front panel for voice reinforcement.

The EA 1128 has an integrated lock anchor point. Just attach a security tether to add an extra level of visual and physical security.

Options:

Built-in wireless microphone receiver and choice of hand and/or lapel VHF microphones (no need for additional equipment just plug and go)

IR voice reinforcement microphone also available

A range of wall and ceiling speakers available for classroom and hall environments

### Specification

4 x Stereo inputs via phono connectors  
2 x Microphone inputs via 6.3mm jack  
2 x 25 Watts @ 8 ohms  
Total Harmonic Distortion < 1% (80Hz~12.5kHz)  
Frequency response (line in): 80Hz~12.5kHz(±2dB)  
Signal to noise ratio (line in): > 77dB (A-weighted)  
Rating input level/Impedance: line in 500mV/47kohms  
Microphone in 15mV/600ohms  
Power consumption (rating condition): < 90W

#### ACCESSORIES INCLUDED:

1 x 2metre 2-phono to 2-phono cable  
1 x 2-phono to 3.5mm mini jack cable  
1 x 2 metre Euro Figure-8 Power cable  
1 x 2 metre UK Figure-8 Power cable  
POWER: 230V Internal Power Supply



Amplifier Dimensions: 430 x 270 x 76mm  
Inner Carton Dimensions: 497 x 365 x 165mm