

Wireless screen Casting transmitter with host

SKU:

EAN:

Edis

FEATURES

| | |
|---|--|
| <ul style="list-style-type: none">● 10-meter Small Meeting Room <p>High-quality metal casing, external dual antennas, supports 1080P resolution. Plug and play, instantly transforming a small screen into a large one. Built-in WiFi module; transmitter and receiver form a local area network, requiring no network configuration or waiting.</p> <ul style="list-style-type: none">● Multi-device access, seamless device switching <p>Supports wireless connection to screen mirroring devices from computers, smartphones, tablets, and other devices. Supports screen mirroring/extended/portrait and landscape modes, ensuring smooth and fast device switching during meetings.</p> <ul style="list-style-type: none">● Efficient connection, easy-to-use computer screen mirroring steps: <p>Wiring: Power the receiver via USB and connect the monitor using a compatible cable.</p> <p>Connection: Plug the transmitter into the computer's USB or Type-C port.</p> <p>Screen Mirroring: Press the button on the transmitter to start screen mirroring.</p> <p>Multi-scenario support, adapting to different needs. Easily handles various scenarios.</p> |  |
|---|--|

SPECIFICATION

| Type | Wireless screen casting USB transmitter | Wireless screen casting USB transmitter with host | Wireless screen casting HDMI transmitter with host | Wireless screen casting HDMI transmitter |
|-------------------------|---|---|---|--|
| Hardware Specifications | TYPE A USB 2.0 X 1 Power, audio/video transmission, pairing, upgrade, and Touch Return are all handled through this interface. | 1 x HDMI output port, 1 x 3.5mm audio jack, 1 x USB port, 1 x 5V 2A power connector | 1x HDMI output port, 1 x Type-C port, 1 x 3.5mm audio jack, 1 x USB port, 1 x 5V 2A power connector | HDMI x 1 for audio/video input; USB x 1 for power, pairing, upgrade, and touch return. |
| Video input resolution | 1920x1200, 1920x1080, 1366x768, 1280x800, 1280x720, 1024x768 | Up to 4K/3840x2160 | Up to 4K/3840x2160 | 1920x1200, 1920x1080, 1366x768, 1280x800, 1280x720, 1024x768 |
| Video output resolution | | Up to 1920x1080 | Up to 1080p/1920x1200 | |
| Frames | Up to 30 frames per second | Up to 30 frames per second | Up to 30 frames per second | Up to 30 frames per second |
| Display ratio | | Geometric progression, 4:3, 16:9 | Geometric progression, 4:3, 16:9, 16:10 | |
| Miracast | support | support | support | support |
| AirPlay | support | support | support | support |
| DLNA | support | support | Not supported | |
| Extend your desktop | support | support | support | support |

wireless screen mirroring

| | | | | |
|---|--|--|---|--|
| Simultaneously displays the number of source ends | | Maximum 1 channel | Maximum 2 channel | |
| Number of simultaneous access sources | | Maximum 8 channels | Maximum 16 channels | |
| Display mode | | Single screen | Single screen and dual screen | |
| Wireless network card | | STA 5G/2.4G dual-band network card module, built-in | STA 5G/2.4G dual-band network card module, built-in | |
| Audio output | 44.1kHz/48kHz/16bit PCM, Stereo | 44.1kHz/16bit stereo. Audio output via HDMI and 3.5mm analog line-in. | 44.1kHz/16bit stereo. Audio output via HDMI and 3.5mm analog line-in. | 44.1kHz/48kHz/16bit PCM, Stereo |
| Audio sharing methods | | Screen sharing: No sound on the computer, but sound is automatically shared on the display. | (1) Screen sharing: If the computer has no sound, the display will automatically share the sound. (2) When sharing multiple screens, there will be no audio mixing; the last screen shared will have sound. (3) When sharing multiple screens, after the last screen shared exits, the sound of the previous screen will be automatically shared. (4) The sound can be switched freely when sharing multiple screens. | |
| Screen rotation | support | support | support | support |
| Wireless encryption protocol | WPA2-PSK | WPA2-PSK | WPA2-PSK | WPA2-PSK |
| How to use | It automatically connects and runs when plugged into a USB, Type-C, or HDMI transmitter, enabling one-click sharing without requiring software installation on your PC or consuming your computer's Wi-Fi. | It automatically connects and runs when plugged into a USB, Type-C, or HDMI transmitter, enabling one-click sharing without requiring software installation on your PC or consuming your computer's Wi-Fi. | It automatically connects and runs when plugged into a USB, Type-C, or HDMI transmitter, enabling one-click sharing without requiring software installation on your PC or consuming your computer's Wi-Fi. | It automatically connects and runs when plugged into a USB, Type-C, or HDMI transmitter, enabling one-click sharing without requiring software installation on your PC or consuming your computer's Wi-Fi. |
| Transmission delay | Average delay less than150ms | Average latency less than 150ms | Average latency less than 150ms | Average delay less than150ms |
| Reverse control method | 1. Supports reverse mouse control; 2. Supports 16-point reverse touch control. | 1. Supports reverse mouse control; 2. Supports 16-point reverse touch control. | 1. Supports reverse mouse control; 2. Supports 16-point reverse touch control. | 1. Supports reverse mouse control; 2. Supports 16-point reverse touch control. |
| Wireless multicast | support | support | support | support |
| Temperature range | Operating temperature: +5°C ~ +40°C; Storage temperature: -20°C ~ +60°C | Operating temperature: +5°C ~ +40°C; Storage temperature: -20°C ~ +60°C | Operating temperature: +5°C ~ +40°C; Storage temperature: -20°C ~ +60°C | Operating temperature: +5°C ~ +40°C; Storage temperature: -20°C ~ +60°C |
| Humidity range | Storage: 0 ~ 90% relative humidity, non-condensing operation; | Storage: 0 ~ 90% relative humidity, non-condensing operation; | Storage: 0 ~ 90% relative humidity, non-condensing operation; | Storage: 0 ~ 90% relative humidity, non-condensing operation; |